

## What would you like to listen to today?



🛞 Bluetooth

apt 🗙



((SiriusXM))



# Media Master<sup>®</sup> 100s

Engineered for marine (and powersports) applications, the MediaMaster<sup>®</sup> 100s Premium Source Unit is built to withstand anything Mother Nature can dish out.

Its beautifully crafted, weatherproof chassis houses an ultra-bright, 3.5-inch full-color LCD display, with separate Day/Night lighting and display themes to keep things easy-to-see, day or night. An intuitive user interface with large, legible text and big, backlit controls make the MM100s easy to use, especially while in motion.

Designed for today's modern media environment, the MM100s features a Digital AM/FM/Weather Band Tuner, Bluetooth<sup>®</sup> connectivity, separate line-level AUX and USB/ iPhone<sup>®</sup> inputs, plus it's SiriusXM-Ready<sup>™</sup>. The MM100s also includes a user-friendly "Favorites" function that allows users to store any combination of AM/FM or Satellite Radio stations, in any order. this makes it super-simple to access your favorite stations, without switching sources or digging through menus.

Equipped with audiophile-quality circuits, the MM100s boasts 8-channels of preamp outputs, delivering crystalclear signals into four separate audio zones, each with its own flexible audio controls.

You can also connect up to three MMR-20 Wired Remotes (sold separately) to add remote control functionality from extended locations.



#### Built-in AM/FM/Weather Band Tuner with RDS

Digital AM/FM Tuner with NOAA weatherband capability. Radio Data System displays channel, category and program information for FM broadcasts, where available. A radio antenna is required (sold separately).



#### SiriusXM-Ready™

Enjoy Commercial-free music, plus the best sports, exclusive talk and entertainment, comedy, news, traffic, weather and more when you add a SiriusXM<sup>®</sup> Connect Vehicle Tuner - sold separately.



#### **USB Input and Charging**

USB 2.0 direct-digital connection for your compatible iPhone<sup>®</sup> or USB storage device.



#### Auxiliary Input

A pair of analog audio inputs permit connection of any audio source with stereo analog outputs.



#### Bluetooth<sup>®</sup> Audio Streaming Allows a Bluetooth<sup>®</sup> equipped smartphone

or portable media device to stream music to your audio system. Wirelessly control Play/ Pause and Track Up/Down functions from your MediaMaster<sup>®</sup> 100s via Bluetooth<sup>®</sup>.



#### Advanced AptX<sup>®</sup> Codec

Delivers maximum audio fidelity from compatible Bluetooth<sup>®</sup> streaming devices.

#### MediaMaster® Accessories



MMR-20 Round Wired Remote 2.36-in. (360 mm) Wired, non-display remote for MM100s



### MMR-10W Wireless Remote

Wireless key-fob style remote for MM100s



MMC-6 Remote Cable 6-foot cable for MMR-20 wired remote MMC-25 Remote Cable 25-foot cable for MMR-20 wired remote MMC-2Y Remote Cable Y-Splitter

Y-adaptor cable for MMC-6 and MMC-25 remote cables



©2016 JL Audio, Inc. • "JL Audio", "Ahead of the Curve" and the JL Audio logo are registered trademarks of JL Audio, Inc. Sirius XM Radio Inc. Sirius, XM and all related marks and logos are trademarks of Sirius XM Radio Inc. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The aptX® word mark and logos are registered trademarks owned by CSR. iPhone® and Lightning™ are registered trademarks of Apple Inc. Use of all trademarks by JL Audio is under license. Due to our policy of continuous product development, all specifications are subject to change without notice.

Electrical Specifications	
Operating Voltage	14.4V DC (10V – 15.9V allowable)
Maximum Current Draw	1.5 A
Standby Current Draw	120 mA
Fuse Value	5 A
Operating Temp Range	-4 F to +158 F (-20 C to +70 C)
Display	
Size / Type	3.5-inch / TFT LCD backlighted
Resolution	320 x 240
Audio Outputs/Inputs	
Output Channels	4 stereo pairs of RCA plugs (3 variable + 1 fixed level)
Output Zones	1 main zone (variable), 2 assignable zones (variable) and 1 fixed level zone
Maximum Output Voltage	4V RMS (zones 1/2/3), selectable 4V/2V/1V RMS (zone 4)
Output Impedance	250 ohm
Input Channels	1 stereo pair of RCA plugs (2V/1V RMS input sensitivity)
Tuner	
Tuner FM Tuner with RDS	87.5 MHz to 107.9 MHz (0.2 MHz step)
	87.5 MHz to 107.9 MHz (0.2 MHz step) 530 kHz to 1710 kHz (10 kHz step)
FM Tuner with RDS	
FM Tuner with RDS AM Tuner	530 kHz to 1710 kHz (10 kHz step)
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step)
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step)
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth*	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile Core Specification	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile Core Specification Codec	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR SBC, aptX®
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile Core Specification Codec	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR SBC, aptX®
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth* Profile Core Specification Codec Connection Range	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR SBC, aptX <sup>®</sup> Up to 35 ft / 11 m
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile Core Specification Codec Connection Range USB	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR SBC, aptX® Up to 35 ft / 11 m USB 2.0 host
FM Tuner with RDS AM Tuner NOAA Weather Band Tuner Favorites Bluetooth® Profile Core Specification Codec Connection Range USB Interface	530 kHz to 1710 kHz (10 kHz step) 162.400 MHz to 162.550 MHz (0.025 MHz step) 18 presets across all tuners A2DP v1.2, AVRCP v1.4 Version 2.1 + EDR SBC, aptX° Up to 35 ft / 11 m USB 2.0 host 1 A

Mounting Hole W x H 4.70 in. x 3.25 in. (119.50 mm x 82.50 mm)

**www.jlaudio.com** 10369 North Commerce Parkway • Miramar, Florida • 33025 • USA