

RD400/4: 4-Channel Amplifier

Utilizing our exclusive NexD™ switching technology, the compact RD400/4 amplifier is engineered to deliver loads of audio output power with incredible efficiency and low distortion. With its modern industrial design and small size, this little powerhouse churns out 100 watts of crystal-clear audio from each of its four channels and is fully bridgeable, so it can be used as a 3-channel amplifier, or as a 2-channel amplifier producing a whopping 200W x 2 into 4 ohms.

For convenience, the RD400/4's controls are located on top, beneath a protective cover, with all connections placed along one side of its chassis. Studio-grade signal processing features include high or low-pass filters (defeatable) for

each channel pair, and dual-range, differential-balanced inputs capable of accepting most input signals. Automatic turn-on (signal or DC-offset sensing) options are standard, along with all-new input type switches for easier bridging without needing Y-adaptors. A set of preamp outputs make passing signals to another amplifier an easy affair.

All-new LED-clipping indicators are also on-board to simplify installation and setup. This time-saving feature lets you quickly and accurately set your amplifier's input sensitivity settings, with no special equipment needed. The top-mounted, dual-color LED light strip vibrantly reports the overall status and condition.

Mo	odel	Description	Continuous Power (RMS Method)	THD+N at Rated Power	Frequency Response	Damping Factor	Dimensions H x W x D
RD 400/4 Amplifier							
RD4	100/4	Class D, Full-Range 4-Channel Amplifier	75W RMS x 4 @ 4 ohms 100W RMS x 4 @ 2 ohms Bridged: 200W RMS x 2 @ 4 ohms (Ratings at 14.4V supply voltage)	<1%	12 Hz - 22 kHz (+0, -1dB)	>150 @ 4 ohms per ch./ 50 Hz >75 @ 2 ohms per ch. / 50 Hz	2.13 in x 9.78 in x 6.96 in 54 mm x 248 mm x 177 mm





Get Maximum Performance...Plus Benefits

Have an Authorized JL Audio Retailer install your RD amplifier with a qualifying JL Audio Power Connection System and receive one additional year of amplifier warranty coverage.

 $\hbox{*Terms and conditions apply. Visit jlaudio.com for complete warranty details.}$



©2016 JL Audio, Inc. • "JL Audio", "Ahead of the Curve" and the JL Audio logo are registered trademarks of JL Audio, Inc. Due to our policy of continuous product development, all specifications are subject to change without notice.